

HPF



*** [8IH-500/T2000]**

: A RF signal filter that filters out every frequency except those within the band from 500 MHz to 2 GHz.

*** [8IH-2000/T6000]**

: A RF signal filter that filters out every frequency except those within the band from 2 GHz to 6 GHz.

Item	8IH-500/T2000	8IH-2000/T6000
Cutoff Frequency	500MHz	2000MHz
Upper Passband Limit	2000MHz	6000MHz
Insertion Loss (Max.)	1.2dB	1.5dB
Rejections (Min.)	55dB @ 420MHz	55dB @ 1670MHz
VSWR (Max.)	1.5 : 1	1.5 : 1